

BRIMAR

**R. E. T. M. A.
REGISTRATION DATA**

TYPE 4EN4
DATE 10th March '58
ISSUED

TYPE 4EN4.

The 4EN4 is a miniature medium- μ triode intended primarily for use as a radio frequency amplifier in VHF television tuners. The electrical characteristics are similar to those of each section of the 6BZ7.

MECHANICAL DATA.

Coated unipotential cathode.
Outline drawing..... 5-2 Bulb..... T-5 $\frac{1}{2}$
Base..... E7-1 Miniature Button 7-pin
Maximum diameter..... $\frac{3}{4}$ "
Maximum overall length..... 2 $\frac{1}{8}$ "
Maximum seated height..... 1 $\frac{7}{8}$ "
Pin Connections..... Basing 7EG
Pin 1 - Cathode. Pin 5 - Plate.
Pin 2 - Grid. Pin 6 - Cathode.
Pin 3 - Heater. Pin 7 - Grid.
Pin 4 - Heater.
Mounting position..... Any

ELECTRICAL DATA.Direct Inter-electrode Capacitances - with external shield.

Grid to plate: (g1 to p)..... 1.244F
Input: g1 to (h+k)..... 3.244F
Output: p to (h+k)..... 1.444F
Heater to cathode: (h to k)..... 2.844F

Ratings Design Centre Values.

Heater voltage (A.C. or D.C.)..... 4.2 volts
Maximum heater-cathode voltage.....
Heater positive with respect to cathode..... 100 volts
Heater negative with respect to cathode..... 100 volts
Maximum plate voltage..... 250 volts
Maximum positive D.C. grid voltage..... 0 volts
Maximum plate dissipation..... 2.0 watts
Maximum D.C. cathode current..... 20milli
amperes
Maximum grid circuit resistance..... 0.5Megohms

BRIMAR

R.E.T.M.A. REGISTRATION DATA (CONTINUED)

TYPE.....4BN4

Typical Operating Conditions and Characteristics, class A1
Amplifier.

Heater voltage (A.C. or D.C.).....	4.2 volts
Heater current.....	0.3 amperes
Plate voltage.....	150 volts
Cathode-bias resistor.....	220 ohms
Plate resistance (approximately).....	6300 ohms
Transconductance.....	6800 microhms
Plate current.....	9.0 milli amperes
Grid voltage, approximate.....	
I _b = 100 Microamperes.....	-6 volts
Amplification factor.....	43