


TYPE 7R7

(LOCTAL BASE)

DOUBLE DIODE

R.F. PENTODE



The BRIMAR type 7R7 is a multiple valve of "all glass" construction designed for simultaneous operation as detector and I.F. or L.F. amplifier in radio receivers. The pentode section has semi-vari-mu characteristics and A.V.C. may be applied.

RATINGS

Heater Voltage	...	6.3 volts
Heater Current	...	0.3 amp.
Anode Voltage	...	250 volts max.
Anode Dissipation	...	2.0 watts max.
Screen (G2) Voltage	...	100 volts max.
Screen Dissipation	...	0.25 watt max.

OPERATING CHARACTERISTICS

Anode Voltage	...	100	250	volts
Anode Current	...	5.5	5.7	mA
Screen Voltage	...	100	100	volts
Screen Current	...	2.0	1.7	mA
Control Grid (G1) Voltage	...	-1.0	-1.0	volt
Cathode Bias Resistor	...	150	150	ohms
Anode Impedance	...	0.35	1.0	meg.
Mutual Conductance	...	3.0	3.2	mA/V
Control Grid Voltage	...	-16	-20	volts

(For Anode current cut-off)

INTER-ELECTRODE CAPACITANCES

Input (Control Grid to all except Anode)	...	5.6	pF
Output (Anode to all except Control Grid)	...	5.3	pF
Control Grid to Anode	...	0.004	pF max.

