



SUBMINIATURE TUBES



TYPE	CONSTRUCTION	TYPICAL APPLICATION	HTR or FILAMENT			TERM. CONN.	MAX. DIMENSIONS Inches			PLATE VOLTS	GRID 1 VOLTS	GRID 2 VOLTS	GRID 3 VOLTS	PLATE CURR. ma.	GRID 2 CURR. ma.	AMP. FACT.	PLATE RESIST. meg.	MUT. COND. μ mas	OUTPUT milliwatts	LOAD RESIST. meg.	TYPE
			Volts	Ma.	Type		Length	Width	Thick-ness												
1AD4¹	Pentode	R-F Amplifier	1.25	100	Fil	5A	1.5	.385	.285	45	Rg = 2 meg.	45		2.8	0.8		0.5	2000			1AD4¹
1AE5	Heptode	Mixer	1.25	60	Fil	6A	1.5	.400	.300	45	Rg = 0.2 meg.	45	0	0.9	2		0.2	200 ³			1AE5
1AG4	Pentode	Power Amp.	1.25	40	Fil	5J	1.5	.385	.285	41.4	—3.6	41.4		2.4	0.6		0.18	1000	35	0.012	1AG4
1AG5	Diode-Pent.	Det.-Amplifier	1.25	30	Fil	68	1.5	.385	.285	45	Rg = 5 meg.	45		0.8	0.25		0.26	350			1AG5
1AH4¹	Pentode	R-F Amplifier	1.25	40	Fil	5A	1.5	.385	.285	45	Rg = 5 meg.	45		0.75	0.2		1.5	750			1AH4¹
1V6	Triode-Pent.	Converter	1.25	40	Fil	7BC	1.5	.410	.285	45	Rg = 5 meg.	45		0.40	0.15		1.0	200 ³	Eb Triode = 45 lb Triode = 0.4 ma.		1V6
2E31¹ 2E32¹⁻²	Pentode	R-F Amplifier	1.25	50	Fil	5D	1.5	.385	.285	22.5	0	22.5		0.4	0.3		0.35	500			2E31¹ 2E32¹⁻²
2E35 2E36²	Pentode	Power Amp.	1.25	30	Fil	5B	1.5	.385	.285	45	—1.25	45		0.6	0.11		0.25	525	6	0.1	2E35 2E36²
2G21 2G22²	Triode-Hept.	Converter	1.25	50	Fil	7B	1 1/16	.385	.285	22.5	Rg = 50,000	22.5	0	0.2	0.3		0.5	60 ³	Eb Triode = 22.5 lb Triode = 1 ma.		2G21 2G22²
CK501AX	Pentode	Voltage Amp.	1.25	30	Fil	5J	1.5	.385	.285	45	0	45		0.65	0.25		1.0	750	45 ⁴		CK501AX
CK502AX	Pentode	Power Amp.	1.25	30	Fil	5J	1.5	.385	.285	45	—1.25	45		0.6	0.15		0.2	550	6	0.1	CK502AX
CK503AX	Pentode	Power Amp.	1.25	30	Fil	5J	1.5	.385	.285	45	—2	45		0.8	0.25		0.35	550	9.5	0.05	CK503AX
CK505AX	Pentode	Voltage Amp.	0.625	30	Fil	5J	1.25	.385	.285	22.5	—0.625	22.5		0.125	0.040		1.1	180	38 ⁴		CK505AX
CK506AX	Pentode	Power Amp.	1.25	50	Fil	5J	1.5	.385	.285	45	—4.5	45		1.25	0.4		0.12	500	25	0.03	CK506AX
CK507AX	Pentode	Power Amp.	1.25	45	Fil	5J	1.5	.385	.285	45	—2	45		0.9	0.3		0.3	575	11	0.05	CK507AX
CK509AX	Triode	Voltage Amp.	0.625	30	Fil	4B	1.25	.385	.285	45	0			0.15			0.15	160	16 ⁴		CK509AX
CK510AX	Dble-Tetr.	Voltage Amp.	0.625	50	Fil	7D	1.25	.400	.285	45	0			0.06			0.5	65	150 ⁵		CK510AX
CK511X	Pentode	Voltage Amp.	1.25	50	Fil	6C	1.75	Dia. = .550		45	0	45		0.24	0.2		0.22	220	30 ⁴	1.0	CK511X
CK512AX	Pentode	Voltage Amp.	0.625	20	Fil	5J	1.25	.385	.285	22.5	—0.625	22.5		0.125	0.040		1.25	160	37 ⁴		CK512AX
CK515BX	Triode	Voltage Amp.	0.625	30	Fil	4B	1.19	Dia. = .315		45	0			0.15		24		160	16 ⁴	1.0	CK515BX
CK516AX	Triode	Voltage Amp.	0.625	20	Fil	5M	1.25	.385	.285	22.5	—0.625			0.15			0.05	200	7.5 ⁴	1.0	CK516AX
CK518AX¹	Pentode	Power Amp.	1.25	30	Fil	5E	1.515	.380	.290	45	—2	45		0.8	0.25		0.35	550	9.5	0.5	CK518AX¹
CK520AX	Pentode	Power Amp.	0.625	50	Fil	5J	1.25	.385	.285	45	—2.5	45		0.24	0.075		1.0	150	3.5	0.15	CK520AX
CK521AX	Pentode	Power Amp.	1.25	50	Fil	5J	1.5	.385	.285	22.5	—3	22.5		0.8	0.22		0.22	400	6	0.02	CK521AX
CK522AX	Pentode	Power Amp.	1.25	20	Fil	5J	1.5	.385	.285	22.5	0	22.5		0.3	0.08		0.6	450	1.2	0.2	CK522AX
CK523AX	Pentode	Power Amp.	1.25	30	Fil	5J	1.5	.385	.285	22.5	—1.2	22.5		0.3	0.075		0.3	360	2.5	0.075	CK523AX
CK524AX	Pentode	Power Amp.	1.25	30	Fil	5J	1.5	.385	.285	15	—1.75	15		0.45	0.125		0.2	300	2.2	0.03	CK524AX
CK525AX	Pentode	Power Amp.	1.25	20	Fil	5J	1.5	.385	.285	22.5	—1.2	22.5		0.25	0.06		0.33	325	2.2	0.06	CK525AX
CK526AX	Pentode	Power Amp.	1.25	20	Fil	5J	1.5	.385	.285	22.5	—1.5	22.5		0.45	0.12		0.22	400	3.75	0.05	CK526AX
CK527AX	Pentode	Power Amp.	1.25	15	Fil	5J	1.5	.385	.285	22.5	0	22.5		0.1	0.025		1.8	225	0.75	0.3	CK527AX
CK528AX¹	Pentode	Power Amp.	1.25	20	Fil	5E	1.515	.390	.290	22.5	0	22.5		0.3	0.08		0.6	450	1.2	0.2	CK528AX
CK529AX¹	Pentode	Power Amp.	1.25	20	Fil	5E	1.515	.390	.290	15	—1.25	15		0.32	0.075		0.3	350	1.6	0.05	CK529AX¹
CK531DX	Pentode	Power Amp.	1.25	20	Fil	5J	1.25	.285	.220	15	—1.5	15		0.30	0.090		0.25	275	1.6	0.06	CK531DX
CK532DX	Pentode	Power Amp.	1.25	15	Fil	5J	1.25	.285	.220	22.5	0	22.5		0.40	0.125		0.18	450	1.8	0.1	CK532DX
CK533AX	Pentode	Power Amp.	1.25	15	Fil	5J	1.5	.385	.285	22.5	0	22.5		0.36	0.09		0.5	400	1.8	0.075	CK533AX
CK534AX	Pentode	Voltage Amp.	0.625	15	Fil	5J	1.25	.385	.285	15	—0.625	15		0.0047	0.0014		12	20	30 ⁴	2.2	CK534AX
CK535AX	Pentode	Power Amp.	1.25	20	Fil	5J	1.5	.385	.285	15	—1.25	15		0.32	0.075		0.3	350	1.6	0.05	CK535AX
CK536AX¹	Pentode	Power Amp.	1.25	15	Fil	5E	1.5	.385	.285	22.5	0	22.5		0.36	0.09		0.5	400	1.8	0.075	CK536AX¹
CK537AX¹	Pentode	Power Amp.	1.25	20	Fil	5E	1.515	.390	.290	22.5	—1.5	22.5		0.45	0.12		0.22	400	3.75	0.05	CK537AX¹
CK538DX	Pentode	Voltage Amp.	0.625	15	Fil	5J	1.0	.285	.220	15	—0.625	15		0.0046	0.002		10	18	28 ⁴	2.2	CK538DX

See page 3 for reference notes — See pages 18 and 19 for basing diagrams and terminal connections.
This data is compiled as a Raytheon service to the Field, it is not intended to indicate type availability.