



R10
R11



TYPE R10 (GLASS BUTTON BASE) MINIATURE HIGH VOLTAGE RECTIFIER




The BRIMAR type R10 is an indirectly heated half-wave rectifier of the "all glass" construction, fitted with a miniature type base. It is particularly suitable for use in portable oscilloscopes and may be used in television power supplies of the "line fly-back" type.

RATINGS


Heater Voltage	...	...	...	...	...	4.0 volts
Heater Current	...	...	...	...	...	0.5 amp.
Peak Inverse Voltage (No Load)	...	...	...	...	...	15.5 KV. max.
Peak Inverse Voltage (Full Load)	...	...	...	...	...	12.5 KV. max.
Peak Anode Current	...	...	...	...	...	40 mA max.
Supply Frequency	...	...	...	...	...	100 Kc/s max.

CHARACTERISTICS AS HALF-WAVE RECTIFIER

R.M.S. Input (DELAYED SWITCHING)	...	...	...	...	...	5.5. KV. max.
R.M.S. Input (SIMULTANEOUS SWITCHING)	...	...	...	...	...	3.5 KV. max.
Series Anode Impedance	...	...	...	...	...	62,000 ohms min.
Rectified Current	...	...	...	...	...	5.0 mA max.



TYPE R11 (ENGLISH BASE) HIGH VOLTAGE RECTIFIER



RATINGS

Heater Voltage	...	...	...	...	...	4.0 volts
Heater Current	...	...	...	...	...	1.1 amp.
Peak Inverse Voltage (No Load)	...	...	...	...	...	14 KV. max.
Peak Inverse Voltage (Full Load)	...	...	...	...	...	12.5 KV. max.
Peak Anode Current	...	...	...	...	...	350 mA max.
Supply Frequency	...	...	...	...	...	60 cps. max.

CHARACTERISTICS AS HALF-WAVE RECTIFIER

R.M.S. Input	...	...	...	...	...	5.0 KV. max.
Series Anode Impedance	...	...	...	...	...	4,000 ohms min.
Rectified Current	...	...	...	...	...	50 mA max.
Reservoir Condenser	...	...	...	...	...	1.0 μ F max.