



OY4

OY4

HALF-WAVE GAS RECTIFIER


IONICALLY HEATED, STARTER - ELECTRODE TYPE

DATA**General:**

Cathode.	Ionically Heated
Tube Voltage Drop (Approx.).	12 volts
Maximum Overall Length	2-5/8"
Maximum Seated Length.	1-31/32 ± 3/32"
Maximum Diameter	1-5/16"
Bulb	MT8G
Base	Small-Wafer Octal 5-Pin

Basing Designation for BOTTOM VIEW

Pin 1 - Shell

Pin 3 - Starter
Electrode

Pin 5 - Anode

Pin 7[□] - CathodePin 8[□] - Cathode

□ Pins 7 and 8 must be tied together at socket.

HALF-WAVE RECTIFIER**Maximum Ratings, Design-Center Values:**

PEAK INVERSE ANODE VOLTAGE.	300	max.	volts
PEAK ANODE CURRENT.	500	max.	ma
DC OUTPUT CURRENT :	{ 75	max.	ma
	{ 40	min.	ma

Typical Operation With Capacitor-Input Filter:

Minimum RMS Starting Voltage*	100	volts
DC Output Current	75	ma
Minimum Series Anode Resistance [▲]	50	ohms

RF filter circuits placed close to socket terminals are required to reduce rectifier noise.

* When starter electrode is connected to anode through a 10-megohm resistor bypassed with a 0.002- μ f capacitor.[▲] For 117-volt line operation.