


Replacement Type

TYPE 1629

(OCTAL BASE)

“MAGIC EYE”

TUNING INDICATOR



CHARACTERISTICS

Heater Voltage	...	...	...	12.6	volts
Heater Current	...	...	...	0.15	amp.
Anode Supply Voltage	...	...		100 200 250	volts
Anode Load Resistor	...	...		0.5 1.0 1.0	meg.
Anode Current *	...	...	...	0.2 0.2 0.24	mA
Target Voltage	...	...	...	100 200 250	volts
Target Current *	...	...	...	1 3 4	mA
Grid Voltage	...	...	...	-3.3 -6.5 -8	volts

(For 0° shadow angle.)

* For 90° shadow angle, grid voltage zero.