

PHILIPS

Current regulators
Régulateurs de courant
Stromregler

329	340
19 ..	

Type	I (A)	V (V)	Current tolerances from tube to tube Tolérances de courant de tube à tube Stromtoleranzen von Röhre zu Röhre			Max. dimensions in mm Dimensions max. en mm Max. Abmessungen in mm		
			V (V)	I _{min}	I _{max}	l	l ⁽¹⁾	ø.
329	1,15	10-30	20	1,08 A	1,22 A	119	101	34
340	5,9	3-10	7	5,5 A	6,3 A	156	-	53
1904	0,1	30-80	60	96 mA	104 mA	100 ⁽²⁾	92 ⁽³⁾	39
1905	1	2-6	4	960 mA	1,04 A	100	-	35
1908	0,8	5-15	5 7 15	740 mA 760 mA 770 mA	820 mA 860 mA 860 mA	107	89	35
1909 1909A	0,625	5-45	30	595 mA	655 mA	123	105	56
1910	1,4	5-15	5 8,5 15	1,3 A 1,35 A 1,35 A	1,5 A 1,5 A	110	92	35
1913	2	4-12	8	1,92 A	2,08 A	129	-	41
1918-01	0,1	4-10	7	97 mA	108 mA	67	-	21,5
1923	0,43	15-45	30	410 mA	450 mA	98	-	39
1926 ⁽⁴⁾	0,18	8-26	16	168 mA	192 mA	101	-	33
1927	0,18	40-120	80	172 mA	188 mA	138	120	40,5
1928	0,18	80-240	160	172 mA	188 mA	147	129	40,5
1941	0,3	80-200	140	289 mA	311 mA	162 ⁽⁵⁾ 154 ⁽⁶⁾	144 ⁽⁵⁾	53
1945 ⁽⁴⁾	0,275	80-120	100	263 mA	283 mA	115	-	38

1) Length without pins; longueur sans broches
Länge ohne Stiften

2) Swan
3) 3-p
4) Resistance tube; tube de résistance; Widerstandsröhre

5) A
6) Edison

PHILIPS

Current regulators
Régulateurs de courant
Stromregler

329 340

19 ..

Type	I (A)	V (V)	Current tolerances from tube to tube Tolerances de courant de tube à tube Stromtoleranzen von Röhre zu Röhre			Max. dimensions in mm Dimensions max. en mm Max. Abmessungen in mm		
			V (V)	Imin	Imax	l	l ⁽¹⁾	ø
329	1,15	10-30	20	1,08 A	1,22 A	119	101	34
340	5,9	3-10	7	5,5 A	6,3 A	156	-	53
1904	0,1	30-80	60	96 mA	104 mA	100 ⁽²⁾ 110 ⁽³⁾	- 92 ⁽³⁾	39
1905	1	2-6	4	960 mA	1,04 A	100	-	35
1908	0,8	5-15	5 7 15	740 mA 760 mA 770 mA	820 mA 860 mA 860 mA	107	89	35
1909 1909A	0,635	5-45	30	605 mA	665 mA	123	105	56
1910	1,4	5-15	5 8,5 15	1,3 A 1,35 A 1,35 A	1,5 A 1,5 A 1,5 A	110	92	35
1913	2	4-12	8	1,92 A	2,08 A	129	-	41
1918-01	0,1	4-10	7	97 mA	108 mA	67	-	21,5
1923	0,43	15-45	30	410 mA	450 mA	98	-	39
1926 ⁽⁴⁾	0,18	8-26	16	168 mA	192 mA	101	-	33
1927	0,18	40-120	80	172 mA	188 mA	138	120	40,5
1928	0,18	80-240	160	172 mA	188 mA	147	129	40,5
1941	0,3	80-200	140	289 mA	311 mA	162 ⁽⁵⁾ 154 ⁽⁶⁾	144 ⁽⁵⁾ -	53
1945 ⁽⁴⁾	0,275	80-120	100	263 mA	283 mA	115	-	38

1) Length without pins; longueur sans broches;
Länge ohne Stiften

5) A

2) Swan
3) 3-p
6) Edison

4) Resistance tube; tube de résistance; Widerstandsröhre




329 340

19 ..

PHILIPS

Current regulators
Régulateurs de courant
Stromregler

329




Base, Culot, Socket : 3-p.
Socket, Support, Fassung: 40465

1904
1908
1909
1910




3-p
40465

1909A




3-p
40465

1927
1928
1941



A
40465

1926
1945



Base, Culot, Socket:

P.

340
1905
1913
1923
1941



EDISON

1918-01



EDISON MIGNON

1904



S.B.C.


329 340

19 ..

PHILIPS


Current regulators
Régulateurs de courant
Stromregler

1927
1928
1941



A
40465

1909A




3-p
40465

1904
1908
1909
1910



3-p
40465

329



3-p
40465

Base, Culot, Socket :
Socket, Support, Fassung:

1904



S.B.C.

1918-01



EDISON MIGNON

340
1905
1913
1923
1941



EDISON

1926
1945



P

Base, Culot, Socket:



1904	1905	1908	1909	1909A	1910	1913	1918-01
1923	1926	1927	1928	1941	1945	329	340
page			sheet		date		
1			1		1955.07.07		
2			1		1960.11.11		
3			2		1955.07.07		
4			2		1960.11.11		
5			FP		1999.09.18		