



35W4

35W4 HALF-WAVE VACUUM RECTIFIER


MINIATURE TYPE

GENERAL DATA

Electrical:	Without Panel Lamp	With No. 40 or No. 47 Panel Lamp	
Heater, for Unipotential Cathode:			
Voltage (AC or DC):			
Entire Heater (pins 3 & 4) . . .	35	32	volts
Panel-Lamp Section (pins 4 & 6) . . .	7.5	5.5	volts
Current { between pins 3 & 4 . . .	0.15	-	amp
{ between pins 3 & 6 . . .	-	0.15	amp

Mechanical:

Mounting Position	Any
Maximum Overall Length	2-5/8"
Maximum Seated Length	2-3/8"
Length from Base Seat to Bulb Top (Excluding tip)	2" ± 3/32"
Maximum Diameter	3/4"
Bulb	T-5-1/2
Base	Small-Button Miniature 7-Pin
Basing Designation for BOTTOM VIEW	58Q
Pin 1—No Connection	Pin 6—Heater Tap
Pin 2—No Connection	Pin 7—Cathode
Pin 3—Heater	Panel-Lamp Heater
Pin 4—Heater	Section is be-
Pin 5—Plate	tween pins 4 & 6



HALF-WAVE RECTIFIER

Maximum Ratings, Design-Center Values:

PEAK INVERSE PLATE VOLTAGE	330 max.	volts
PEAK PLATE CURRENT	600 max.	ma
DC OUTPUT CURRENT:		
With Panel Lamp & { No Shunting Resistor.	60 max.	ma
{ Shunting Resistor . . .	90 max.	ma
Without Panel Lamp	100 max.	ma
PANEL-LAMP-SECTION VOLTAGE (RMS):		
When panel lamp fails	15 max.	volts
PEAK HEATER-CATHODE VOLTAGE:		
Heater negative with respect to cathode.	330 max.	volts
Heater positive with respect to cathode.	330 max.	volts

Typical Operation with No.40 or No.47 Panel Lamp in
Accompanying Half-Wave Circuit with Capacitor-Input Filter:

AC Plate-Supply Volt. (RMS).	117	117	117	117	volts
Filter-Input Capacitor	40	40	40	40	μf
Min. Total Effective					
Plate-Supply Impedance	15	15	15	15	ohms
Panel-Lamp Shunting Res.	-	300	150	100	ohms
DC Output Current	60	70	80	90	ma

← Indicates a change.

35W4



35W4

HALF-WAVE VACUUM RECTIFIER

Typical Operation Without Panel Lamp in Conventional Half-Wave Circuit with Capacitor-Input Filter:

AC Plate-Supply Voltage (RMS).	117	volts
Filter-Input Capacitor	40	μ f
Min. Total Effective Plate-Supply Imped.	15	ohms
DC Output Current	100	ma
DC Output Voltage at Input to Filter (Approx.):		
→ At half-load current (50 ma.)	135	volts
At full-load current (100 ma.)	120	volts
Voltage Regulation (Approx.):		
→ Half-load to full-load current	15	volts


Maximum Circuit Values:

Panel-Lamp Shunting Resistor:*

For dc output current of	70 ma.	800 max.	ohms
	80 ma.	400 max.	ohms
	90 ma.	250 max.	ohms

*Required when dc output current is greater than 60 ma.

HALF-WAVE CIRCUIT with No.40 or No.47 Panel Lamp



DROP ACROSS R AND ALL HEATERS (WITH PANEL LAMP) SHOULD EQUAL 117 VOLTS AT 0.15 AMPERE. R_s = SHUNTING RESISTOR REQUIRED WHEN DC OUTPUT CURRENT EXCEEDS 60 MILLIAMPERES

92CS-6626

Devices and arrangements shown or described herein may use patents of RCA or others. Information contained herein is furnished without responsibility by RCA for its use and without prejudice to RCA's patent rights.

→ Indicates a change.



35W4


35W4 OPERATION CHARACTERISTICS HALF-WAVE RECTIFIER

$E_f = 35$ VOLTS BETWEEN PINS No 3 & No 4
(NO TAP CONNECTION)

PLATE VOLTS = 117 RMS

TOTAL EFFECTIVE PLATE-SUPPLY
IMPEDANCE = 15 OHMS

C = CAPACITOR INPUT TO FILTER



MAY 19, 1950

TUBE DEPARTMENT
RADIO CORPORATION OF AMERICA, HARRISON, NEW JERSEY


92CM-6615R1

35W4



35W4

AVERAGE PLATE CHARACTERISTIC



92CM-6305TV