


TUNG-SOL

HALF-WAVE VACUUM RECTIFIER

MINIATURE TYPE



GLASS BULB

SMALL-BUTTON MINIATURE

7 PIN BASE E7-1

OUTLINE DRAWING
JEDEC 5-3

UNIPOTENTIAL CATHODE


HEATER NOMINAL

36 VOLTS 32 VOLTS

0.10±.006 AMP.

AC OR DC

ANY MOUNTING POSITION



BOTTOM VIEW

BASING DIAGRAM
JEDEC 580

THE 36AM3A IS A HALF-WAVE VACUUM RECTIFIER IN THE 7 PIN MINIATURE CONSTRUCTION. IT IS DESIGNED FOR USE IN AC/DC RECEIVERS. FEATURES OF THE TUBE ARE A LOW TUBE-VOLTAGE DROP AND A 100-MILLIAMPERE HEATER.

RATINGS

INTERPRETED ACCORDING TO DESIGN MAXIMUM SYSTEM

HALF-WAVE RECTIFIER

HEATER CURRENT ^A	0.10±.006	AMP.
HEATER VOLTAGE (ENTIRE HEATER - PINS 3 & 4)	36	VOLTS
HEATER VOLTAGE (TAP-SECTION PINS 3 & 6)	32	VOLTS
MAXIMUM PEAK INVERSE PLATE VOLTAGE	365	VOLTS
MAXIMUM PEAK PLATE CURRENT	530	MA.
MAXIMUM DC OUTPUT CURRENT	82	MA.
MAXIMUM PEAK HEATER-CATHODE VOLTAGE:		
HEATER NEGATIVE WITH RESPECT TO CATHODE	350	VOLTS
HEATER POSITIVE WITH RESPECT TO CATHODE	200 ^B	VOLTS

TYPICAL OPERATION IN ACCOMPANYING HALF-WAVE CIRCUIT

CAPACITOR-INPUT FILTER

AC PLATE-SUPPLY VOLTAGE, RMS	120	VOLTS
FILTER-INPUT CAPACITOR	40	μf
TOTAL EFFECTIVE PLATE-SUPPLY RESISTANCE	A	OHMS
DC OUTPUT CURRENT	75	MA.
DC OUTPUT VOLTAGE AT INPUT TO FILTER (APPROX.)	118	VOLTS
TUBE VOLTAGE DROP FOR PLATE MA. = 150	16	VOLTS

^A THE HEATER OF THE 36AM3A IS DESIGNED SO THAT THE HEATER SECTION BETWEEN PIN 4 & 6 IS USED AS A LIMITING RESISTANCE IN THE RECTIFIER PLATE CIRCUIT. (SEE TYPICAL HALF-WAVE CIRCUIT).

THIS TYPE IS NOT DESIGNED FOR USE WITH A PANEL LAMP WHERE THE HEATER SECTION BETWEEN PINS 4 & 6 IS USED AS A PANEL-LAMP SHUNT.

^B THE DC COMPONENT MUST NOT EXCEED 100 VOLTS.

CONTINUED ON FOLLOWING PAGE

CONTINUED FROM PRECEDING PAGE

TYPICAL HALF-WAVE CIRCUIT

