

PREMIUM TUBES — Cont'd

Designed to Meet Military Specifications and Critical Industrial Applications

 Type	Proto-type	Name	Description and/or Difference Between Type and Prototype			Special Tests and Controls										
			Rating or Characteristic	Premium Type	Proto-Type	Shock	Fatigue	Vibration	Glass Strain	RF Noise, Microphonics	Stability	Inoperatives	High-Altitude	Heater-Cycling	Room Temp.	Elevated Bulb Temp.
5726/ 6AL5-W/ 6097	6AL5	Twin Diode*	This type is designed to meet the indicated military specification.			✓	✓	✓	✓	—	✓	✓	✓	✓	—	✓
5727	2D21	Thyratron Tetrode*	Heater-Cathode Type. Relay, grid-controlled rectifier, and pulse-modulator service. Operates in a high-sensitivity circuit directly from a vacuum photo-tube.			✓	✓	✓	✓	—	✓	✓	✓	✓	—	✓
5727/ 2D21-W	2D21	Thyratron Tetrode*	This type is designed to meet the indicated military specification.			✓	✓	✓	✓	—	✓	✓	✓	✓	✓	—
5749	6BA6	Remote-Cutoff Pentode*	Heater-Cathode Type. For high-grain rf or if amplifier service, and automatic-gain-control circuits.			✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	—
5749/ 68A6-W	6BA6	Remote-Cutoff Pentode*	This type is designed to meet the indicated military specification.			✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	—
5750	6BE6	Pentagrid Converter*	Heater-Cathode Type. For renewal use only.			✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	—
5751	12AX7	High-Mu Twin Triode§	This type is designed to meet the indicated military specification.			✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	—
5751-WA	12AX7	High-Mu Twin Triode§	This type is designed to meet the indicated military specification.			✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	—
5814-A	12AU7	Medium-Mu Twin Triode§	Heater Current Amp./Sect.	0.175	0.15	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	—
			Peak H-K Volts	± 100	± 200■											
			Controlled Plate-Current Balance	Yes	No											
5814-WA	12AU7	Medium-Mu Twin Triode§	This type is designed to meet the indicated military specifications.			✓	✓	✓	✓	✓	✓	✓	✓	✓	—	✓
5840	—	Sharp-Cutoff Pentode*	Heater-Cathode Type. Useful as an rf or if amplifier tube in broad-band circuits of mobile and aircraft equipment. Can be used up to 400 Mc. as an rf amplifier.			✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	—
5896	—	Twin Diode*	Heater-Cathode Type. A low-current rectifier and detector at frequencies through the uhf regions.			✓	✓	✓	✓	—	✓	✓	✓	✓	✓	—
5899	—	Semiremote-Cutoff Pentode*	Heater-Cathode Type. For use in age rf and if amplifier circuits up to 400 Mc.			✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	—
5902	—	Beam-Power Tube*	Heater-Cathode Type. For use as an audio-amplifier and series-regulator tube in power supplies.			✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	—
6005	6AQ5	Beam-Power Tube*	Max. Bulb Temperature, °C	225	250	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	—
6005/ 6AQ5-W	6AQ5	Beam-Power Tube*	This type is designed to meet the indicated military specification.			✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	—
6005/ 6AQ5-W/ 6095	6AQ5	Beam-Power Tube*	This type is designed to meet the indicated military specification.			✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	—
6021	—	Medium-Mu Twin Triode*	For general-purpose oscillator and amplifier applications. Each unit has a separate cathode.			✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	—

For key to terminal connections see page 30.

* 7-pin miniature type.

§ 9-pin miniature type.

• Subminiature type with flexible leads.

■ DC component must not exceed 100 volts.



5726/6AL5-W/6097




5727
5727/2D21-W



5749 5749/6BA6-W



5750



5751 5751-WA
5814-A 5814-WA

PREMIUM TUBES — Cont'd

Designed to Meet Military Specifications and Critical Industrial Applications

Cathode		Maximum Dimensions Inches		Class of Service	Maximum Ratings				Operating Conditions and Characteristics								Type	
					Plate Volts	Plate Dissipation Watts	Cathode Current Ma.	Grid-No. 2 Input Watts	Plate Supply Volts	Grid-No. 1 Volts(v) or Cathode Resistance Ohms	Grid-No. 2 Supply Volts	Plate Current Ma.	AC Plate Resistance Ohms	Trans-conductance Micro-mhos	Amplification Factor	Power Output Watts		
Volts	Amps.	Length	Diam.															
6.3	0.3	1 3/4	3/4	Half-Wave Rectifier	For data refer to MIL-E-1/235A specification [▲]												5726/ 6AL5-W/ 6097	
6.3	0.6	2 1/8	3/4	Relay and Grid-Controlled Rectifier Service	Maximum Ratings: Peak Forward Anode Volts, 650 Peak Inverse Anode Volts, 1300 Fault Cathode Amp., 10 Peak Cathode Amp., 0.5 Av. Cathode Amp., 0.1												5727	
6.3	0.6	2 1/8	3/4	Control Service	For data refer to MIL-E-1/83B specification [▲]												5727/ 2D21-W	
6.3	0.3	2 1/8	3/4	Class A ₁ Amplifier	300	3.0	—	0.6	100 250	68 68	100 100	10.8 11	250000 1000000	4300 4400	— —	— —	5749	
6.3	0.3	2 1/8	3/4	Class A ₁ Amplifier	For data refer to MIL-E-1/8 specification [▲]												5749/ 6BA6-W	
6.3	0.3	2 5/16	7/8	Converter Service Separate Excitation	300	1.0	14	1.0	100	—	100	2.6	400000	Osc. Grid Volts (rms.), 10		5750		
6.3 12.6	0.35 0.175	2 5/16	7/8	Class A ₁ Amplifier Each Unit	For data refer to MIL-E-1/10A specification [▲]												5751	
6.3 12.6	0.35 0.175	2 5/16	7/8	Class A ₁ Amplifier Each Unit	For data refer to MIL-E-1/237 specification [▲]												5751-WA	
6.3 12.6	0.35 0.175	2 5/16	7/8	Class A ₁ Amplifier Each Unit	For data refer to MIL-E-1/12A specification [▲]												5814-A	
6.3 12.6	0.35 0.175	2 5/16	7/8	Class A ₁ Amplifier Each Unit	For data refer to MIL-E-1/238A specification [▲]												5814-WA	
6.3	0.15	1 3/8†	0.4	Class A ₁ Amplifier	165	1.1	16.5	0.55	100	150	100	7.5	260000	5000	—	—	5840	
6.3	0.3	1 3/8†	0.4	Full-Wave Rectifier	For data refer to MIL-E-1/174C specification [▲]												5896	
6.3	0.15	1 3/8†	0.4	Class A ₁ Amplifier	165	1.1	16.5	0.55	100	120	100	7.2	260000	4500	Grid-No. 1 Volts for Cutoff, -14		5899	
6.3	0.45	1 3/4†	0.4	Class A ₁ Amplifier	165	4.0	50	1.0	110	270	110	30	15000	4200	Grid-No. 1 Volts for Cutoff, -40		5902	
6.3	0.45	2 5/8	3/4	Class A ₁ Amplifier	275	11	—	2.2	180 250	— 8.5v -12.5v	180 250	29 45	58000 52000	3700 4100	— —	2 4.5	6005	
6.3	0.45	2 5/8	3/4	Class A ₁ Amplifier	For data refer to MIL-E-1/13B specification [▲]												6005/ 6AQ5-W	
6.3	0.45	2 5/8	3/4	Class A ₁ Amplifier	For data refer to MIL-E-1/239 specification [▲]												6005/ 6AQ5-W/ 6095	
6.3	0.3	1 3/4†	0.4	Class A ₁ Amplifier Each Unit	165	1.1	—	—	100	150	—	6.5	6500	5400	35	Grid Volts for Cutoff, -6.5		6021

[▲] A copy of this specification may be obtained from the Director of the Armed Services Electro-Standards Agency (ASESA) at Fort Monmouth, New Jersey.

‡ Excluding flexible leads.

