


TUNG-SOL



GLASS BULB
MINIATURE BUTTON
7 PIN BASE E7-1
OUTLINE DRAWING
JEDEC 5-2

TETRODE
MINIATURE TYPE


COATED UNIPOTENTIAL CATHODE

HEATER

6.3 ± 0.6 VOLTS 0.2 AMP. ←

AC OR DC

ANY MOUNTING POSITION



BOTTOM VIEW
BASING DIAGRAM
JEDEC 7EW

THE 6CY5 IS A SHARP-CUTOFF TETRODE IN THE 7-PIN MINIATURE CONSTRUCTION AND IS DESIGNED FOR SERVICE IN VHF TUNERS OF TELEVISION RECEIVERS. EXCEPT FOR HEATER RATINGS AND HEATER WARM-UP TIME, THE 6CY5 IS IDENTICAL TO THE 2CY5, 3CY5 AND 4CY5.

DIRECT INTERELECTRODE CAPACITANCES^A

GRID #1 TO PLATE	0.03	$\mu\mu\text{f}$
INPUT	4.5	$\mu\mu\text{f}$
OUTPUT	3.0	$\mu\mu\text{f}$

RATINGS

INTERPRETED ACCORDING TO DESIGN CENTER SYSTEM

MAXIMUM PLATE VOLTAGE	180	VOLTS
MAXIMUM GRID #2 (SCREEN) SUPPLY VOLTAGE	180	VOLTS
MAXIMUM GRID #2 VOLTAGE	SEE GRID #2 INPUT RATING CHART	
MAXIMUM PLATE DISSIPATION	2.0	WATTS
MAXIMUM GRID #2 DISSIPATION	0.5	WATTS
MAXIMUM GRID #1 (CONTROL GRID) VOLTAGE		
POSITIVE VALUE	0	MA.
MAXIMUM CATHODE CURRENT	20	MA.
MAXIMUM HEATER-CATHODE VOLTAGE		
HEATER POSITIVE WITH RESPECT TO CATHODE	100	VOLTS
HEATER NEGATIVE WITH RESPECT TO CATHODE	100	VOLTS

^A WITH SHIELD #316 CONNECTED TO CATHODE.

→ INDICATES A CHANGE.

CONTINUED ON FOLLOWING PAGE

6CY5

TUNG-SOL

CONTINUED FROM PRECEDING PAGE

TYPICAL OPERATING CONDITIONS AND CHARACTERISTICS

PLATE VOLTAGE	125	VOLTS
GRID #2 VOLTAGE	80	VOLTS
GRID #1 VOLTAGE	-1	VOLTS
PLATE RESISTANCE	0.1	MEGOHM
TRANSCONDUCTANCE	8 000	μ MHOS
GRID #1 CUTOFF BIAS ^C	-6	VOLTS
PLATE CURRENT	10	MA.
GRID #2 CURRENT	1.5	MA.

^C PLATE CURRENT 20 μ A.

