


C6
6D6
6F5



Replacement Type

TYPE **6C6**
(U.X. BASE)
R.F. PENTODE



CHARACTERISTICS


Heater Voltage	...	6.3 volts	Screen Current	...	0.5 mA
Heater Current	...	0.3 amp.	Control Grid (G1) Voltage	...	-3 volts
Anode Voltage	...	250 volts	Anode Impedance	...	1.0 meg.
Anode Current	...	2.0 mA	Mutual Conductance	...	1.2 mA/V
Screen (G2) Voltage	...	100 volts	Cut-off Voltage	...	-7 volts

For further information on characteristics refer to type 6J7G.



Replacement Type


TYPE **6D6**
(U.X. BASE)
VARI-MU R.F. PENTODE



CHARACTERISTICS


Heater Voltage	...	6.3 volts	Screen Current	...	2.0 mA
Heater Current	...	0.3 amp.	Control Grid (G1) Voltage	...	-3 volts
Anode Voltage	...	250 volts	Anode Impedance	...	0.8 meg.
Anode Current	...	8.2 mA	Mutual Conductance	...	1.6 mA/V
Screen (G2) Voltage	...	100 volts	Cut-off Voltage	...	-50 volts

For further information on characteristics refer to type 6U7G.



Obsolete Type

For Information Only
TYPE **6F5**
(OCTAL BASE)
HIGH MU TRIODE



CHARACTERISTICS

Heater Voltage	...	6.3 volts	
Heater Current	...	0.3 amp.	
Anode Voltage	...	250 volt	
Anode Current	...	0.9 mA	
Control Grid Voltage	...	-2 volts	
Anode Impedance	...	66,000 ohms	
Mutual Conductance	...	1.5 mA/V	
Amplification Factor	...	100	