



Current Equipment Type

TYPE ECF82/6U8

MINIATURE

TRIODE PENTODE

FREQUENCY CHANGER



The BRIMAR ECF82/6U8 is a triode-pentode frequency changer featuring a high slope triode and a high input impedance pentode of high slope suitable for use in television receivers for Band III. The high input impedance at 200 Mc/s permits a sensibly constant conversion gain to be obtained over Bands I and III. The low value of C_{ag} for the pentode and C_{ap} , a_t facilitate the reduction of oscillator radiation. The use of low oscillator grid current to obtain the required heterodyne voltage reduces the frequency drift of the oscillator to a minimum.

Heater Current ...	...	...	...	...	...	...	...	...	0.45 amp.
Heater Voltage ...	...	...	...	...	...	...	...	...	6.3 volts (nom.)

RATINGS

Heater—Cathode Potential (cathode positive) ...	...	...	...	...	...	...	...	220 volts max.
Heater—Cathode Potential (cathode negative) ...	...	...	...	...	...	...	...	90 volts max.
Anode Voltage ($I_a = 0$) ...	...	...	...	...	...	...	...	550 volts max.
Anode Voltage ...	...	...	...	...	...	...	...	300 volts max.
Screen (g_2) Voltage ...	...	...	...	...	...	...	...	300 volts max.
Anode Dissipation ...	...	...	...	...	...	...	...	2.8 watts max.
Screen Dissipation ...	...	...	...	...	...	...	...	0.5 watts max.
Positive D.C. Grid No. 1 Voltage ...	...	...	...	...	...	...	...	0 volts max.
Cathode Current ...	...	...	...	...	...	...	...	20 mA max.
Grid Resistance ...	...	...	...	...	...	...	...	3 megohm max.

CHARACTERISTICS

	Triode	Pentode
Anode Voltage ...	150	250 volts
Screen Voltage ...	—	110 volts
Cathode Bias Resistor ...	56	68 ohms
Anode Current ...	18	10 mA
Screen Current ...	—	3.5 mA
Mutual Conductance ...	8.5	5.2 mA/V
Anode Impedance (approx.) ...	5	400 k ohms
Amplification Factor ...	40	—
Grid No. 1 Voltage (for $I_a = 10\mu A$) ...	—12	—10 volts

TYPICAL OPERATION AS MIXER

	Triode	Pentode
Anode Voltage ...	100	170 volts
Screen Voltage ...	—	110 volts
Cathode Bias Resistor ...	0	680 ohms
Grid Leak Resistor ...	27	100 k ohms
Anode Current ...	7.0	5.5
Screen Current ...	—	2.0
Heterodyne Voltage ...	—	3.0
Conversion Conductance ...	—	1.6

INTER-ELECTRODE CAPACITANCES *

Pentode Grid No. 1 to Pentode Anode ...	...	...	...	...	0.006 pF
Pentode Input ...	...	...	...	...	5.0 pF
Pentode Output ...	...	...	...	...	3.5 pF
Triode Grid to Triode Anode ...	...	...	...	...	1.8 pF
Triode Grid to Cathode ...	...	...	...	...	2.5 pF
Triode Anode to Cathode ...	...	...	...	...	1.0 pF
Cathode to Heater (either section) approx. ...	...	...	...	...	3.0 pF

* Measured with external shield.