

AMPEREX MERCURY VAPOR RECTIFIER 872-A

FILAMENT

A.C. Voltage	5.0
Current (amperes)	6.75
Preheating Period (Seconds)*	30

*Before plate voltage is applied.

MAXIMUM RATINGS

For Operation at Supply Frequency Up to 150 Cycles

	<u>Condensed Mercury</u> <u>Temperature Range</u>	
	<u>15°C. to 60°C.</u>	<u>15°C. to 50°C.</u>
Peak Inverse Voltage	5000	10000
Peak Plate Current (amperes)	5.0	5.0
Average Plate Current (amperes)*	1.25	1.25
Approx. Tube Voltage Drop	10	10



*Averaged over period of 15 seconds.

MAXIMUM OUTPUTS IN TYPICAL CIRCUITS

	A.C. Input Volts R.M.S.	D.C. Output Volts to Filter	Max. D.C. Load Current Amperes
Single-Phase Full Wave (2 Tubes) . . .	3535*	3180	2.5
Single-Phase Full Wave Bridge (4 Tubes) . . .	7070†	6360	2.5
Three-Phase Half Wave (3 Tubes) . . .	4080‡	4780	3.75
Three-Phase Double Y-Parallel (6 Tubes) . . .	4080‡	4780	7.50
Three-Phase Full Wave (6 Tubes) . . .	4080‡	9570	3.75

*Per Tube. †Total. ‡Per Leg.

NOTE: For Out-Of-Phase Filament Excitation information see "Maximum Peak Plate Current" and "Maximum Average Plate Current", pp. 3 and 4, "General Information and Application Notes" section, "Mercury Vapor High Voltage RECTIFIER TUBES".



AMPEREX
872-A

RECTIFIER CIRCUIT	SINGLE PHASE FULL-WAVE 2 TUBES	SINGLE PHASE FULL-WAVE 4 TUBES	THREE PHASE HALF-WAVE	THREE PHASE DOUBLE-Y	THREE PHASE FULL-WAVE
Conditions assumed for following relations	1. Sine-Wave Supply 2. Balanced Phase Voltages 3. Zero Tube Drop 4. Pure Resistance Load 5. No Filter Used				
NOTE: All rectifier filaments supplied by single phase transformers, with secondaries insulated for voltages greater than the Maximum Peak Inverse Voltage.					
E Average	.450 E_{rms} .318 E_{max}	.900 E_{rms} .636 E_{max}	1.170 E_{rms} .827 E_{max}	1.170 E_{rms} .827 E_{max}	2.34 E_{rms} 1.65 E_{max}
E Inverse	3.14 E_{avg}	1.57 E_{avg}	2.09 E_{avg}	2.09 E_{avg}	1.045 E_{avg}
I Average	.636 I_{max}	.636 I_{max}	.827 I_{max}	1.91 I_{max}	.955 I_{max}
Ripple Frequency	2 X Supply Freq.	2 X Supply Freq.	3 X Supply Freq.	6 X Supply Freq.	6 X Supply Freq.
Ripple Voltage (Rms)	48.3%	48.3%	18.3%	4.2%	4.2%
† Ratio $\frac{K_{va}}{D.C. Output K_w}$	1.57	1.11	1.48	1.48	1.05
† Ratio $\frac{K_{va}}{D.C. Output K_w}$	1.11	1.11	1.21	1.05	1.05

† These ratios assume that a choke input filter is used to maintain the output current substantially constant.