



RADAR TUBES

Miniaturised 8in. diameter Radar Tubes with narrow neck and small deflection angle. Suitable for use with either Transistor or Valve circuits. Long persistence, metal backed screens.

FOCUS Magnetic

DEFLECTION Magnetic—43°.

SCREEN.

*Phosphor	Type 'H'.	Type 'L'.
Fluorescence	Orange.	Orange.
Afterglow	Orange.	Orange.
Persistence	Very Long.	Long.

PHYSICAL DETAILS.

Base	B9A/D.
Anode Cap	CT8 Cavity Type.
Max. Overall Length	426 mm.
Neck Diameter	23 mm. (nom.)
Mounting Position	Any.

For other dimensions see outline drawing overleaf.

BASE CONNECTION

Pin 1—Grid.	Pin 6—I.C.
Pin 2—I.C.	Pin 7—N.C.
Pin 3—Cathode.	Pin 8—I.C.
Pin 4—Heater.	Pin 9—1st Anode.
Pin 5—Heater.	Side Contact—2nd Anode.

HEATER.

Heater Voltage	6.3 volts.
Heater Current	0.3 amps.

RATING.

Max. A ₁ voltage	600 volts.
Max. A ₂ voltage	15 kV.
Min A ₂ voltage	8 kV.
Max. V _{h-k}	200 volts.
Max. R _{g-k}	1.5 MΩ
Max. R _{h-k}	1.0 MΩ

TYPICAL OPERATION.

With Valve Drive.

1st Anode voltage	300 volts.
2nd Anode voltage	12 kV.
V _g for visual cut-off	-60 volts.


With Transistor Drive

1st Anode voltage	100 volts.
2nd Anode voltage	12 kV.
V _g for visual cut-off	-25 volts.

Recommended position of focus coil is 60 mm. in front of the grid.

8A/54HM

8A/54LM



Base
Connections
Underside View
of Base



8A/54HM

8A/54LM

