



RELIABLE CATHODE TYPE SUBMINIATURE TUBES



TYPE	CONSTRUCTION	TYPICAL APPLICATION	HEATER		TERM. CONN.	MAX. DIMENSIONS		PLATE VOLTS	GRID 1 VOLTS	GRID 2 VOLTS	GRID 3 VOLTS	PLATE CURR. ma.	GRID 2 CURR. ma.	AMP. FACT.	PLATE RESIST. meg.	MUT. COND. umhos	TYPE
			Volts	Amps.		Height	Diam.										
CK5702WA	Pentode	RF Amplifier	6.3	0.2	7C	1.5	.400	120	Rk200	120	0	7.5	2.5		0.34	5000	CK5702WA
CK5703WA	Triode	UHF Osc.	6.3	0.2	5G	1.5	.400	120	Rk200			9.0		25		5000	CK5703WA
CK5744WA	Triode	Amp.-HF Osc.	6.3	0.2	5H	1.5	.400	250	Rk500			4.0		70		4000	CK5744WA
CK5783WA	Gas Diode	Volt. Reference	Cold		3A	1 1/4	.400	See Voltage Reference Tube Section for Characteristics									CK5783WA
CK5784WA	Pentode	Mixer-Gated Amp.	6.3	0.2	7A	1.5	.400	120	-2	120	0	5.2	3.5			3200	CK5784WA
CK5787WA	Gas Diode	Volt. Regulator	Cold		3A	2 1/16	.400	See Voltage Regulator Tube Section for Characteristics									CK5787WA
CK5829WA	Dble. Diode	Detector	6.3	.015	7FA	1.5	W = .410 Th = .385	Max. Inverse Peak Voltage = 330 v; Max. Io = 5 ma. per plate									CK5829WA
CK6021 ⁷	Dble. Triode	Voltage Amp.	6.3	0.3	8CF	1 3/4	.400	100	Rk150			6.5		35		5400 (Each Unit)	CK6021 ⁷
CK6110 ⁷	Dble. Diode	FW Rectifier	6.3	0.15	8CH	1 3/4	.400	See Rectifier Tube Section for Characteristics									CK6110 ⁷
CK6111 ⁷	Dble. Triode	Voltage Amp.	6.3	0.3	8CF	1 3/4	.400	100	Rk220			8.5		20		5000 (Each Unit)	CK6111 ⁷
CK6112 ⁷	Dble. Triode	Voltage Amp.	6.3	0.3	8CF	1 3/4	.400	100	Rk1500			0.8		70		1800 (Each Unit)	CK6112 ⁷
CK6152	Triode	Amp.-Osc.	6.3	0.2	7BB	1.5	.400	200	Rk680			12.5		15.5		4000	CK6152

RELIABLE MINIATURE TUBES

TYPE	CONSTRUCTION	TYPICAL APPLICATION	HTR or FILAMENT			BAS-ING	MAX. DIMENSIONS Inches		PLATE VOLTS	GRID 1 VOLTS	GRID 2 VOLTS	GRID 3 VOLTS	PLATE CURR. ma.	GRID 2 CURR. ma.	AMP. FACT.	PLATE RESIST. meg.	MUT. COND. umhos	OUT-PUT watts	LOAD RESIST. ohms	TYPE
			Volts	Amps.	Type		Height	Diam.												
CK5654	Pentode	R-F Amplifier	6.3	0.175	Htr	7BD	1 3/4	3/4	120	Rk200	120		7.5	2.5		0.34	5000			CK5654
CK5670	Dble. Triode	Voltage Amp.	6.3	0.35	Htr	8CJ	1 3/4	7/8	150	Rk240			8.2		35		5500	(Each Unit)		CK5670
CK5686	Pentode	RF-AF Power Amp.	6.3	0.35	Htr	9J	2 3/16	7/8	250	-12.5	250		27	3.0			3300	2.7	9000	CK5686
CK5725	Pentode	Mixer-Gated Amp.	6.3	0.175	Htr	9P	1 3/4	3/4	120	-2	120	0	5.2	3.5			3200			CK5725
CK5726	Dble. Diode	Same as 6AL5	6.3	0.3	Htr	9M	1 3/4	3/4	Max. Peak Inverse = 330v; Max. Io = 9 mdc per Plate.											CK5726
CK5749	Pentode	R-F Amplifier	6.3	0.3	Htr	9X	2 1/8	3/4	250	Rk68	100	0	11	4.2		1.0	4400			CK5749
CK5750	Heptode	Converter	6.3	0.3	Htr	8Z	2 1/8	3/4	250	Rg20k	100	-1.5	2.6	7.5		1.0	475 ⁸			CK5750
CK5751	Dble. Triode	Voltage Amp.	6.3 12.6	0.35 0.175	Htr	9W	2 3/16	7/8	250	-3			1.0		70	0.058	1200	(Each Unit)		CK5751
CK5814	Dble. Triode	Voltage Amp.	6.3 12.6	0.35 0.175	Htr	9W	2 3/16	7/8	250	-8.5			10.5		17	0.0077	2200	(Each Unit)		CK5814
CK6186	Pentode	RF Amplifier	6.3	0.3	Htr	7BD	2 1/8	0.75	250	Rk200	150		7.0	2.0		0.8	5000			CK6186
CK6187	Pentode	Mixer-Gated Amp.	6.3	0.15	Htr	9P	1 3/4	0.75	120	-2	120	0	5.2	3.5			3200			CK6187