

# MARCONI D.C. MAINS VALVES

## DL, Low Magnification, 17/6

DL is a low impedance valve for use as a small output valve, initial L.F. amplifier or oscillator. The high conductance provides a considerable stage gain, so that DL can be recommended where sensitivity is required without the use of a pentode. The output is sufficient for average domestic volume with a moving iron speaker.

### Approximate Operating Data.

| Anode Volts. | Grid Bias. | Anode Current. |
|--------------|------------|----------------|
| 100          | -4         | 10.5 m.a.      |
| 150          | -6         | 18 m.a.        |
| 200          | -8         | 25 m.a.        |

Anode Volts, Anode current curve for DL.

