



ELECTRONIC TUBE REFERENCE

6J10BVR

Voltage - Radio Detector Converter electronic tube

CONSOLIDATED TECHNICAL DATA

1 SECTION

CONSTRUCTION

PENTODE

Ruggedized long-life Russian dual-control high-frequency pentode for RF amplification and frequency conversion. Dual-control construction permits mixer and converter operation in demanding professional equipment.

GENERAL CHARACTERISTICS

BASE DESIGNATION	—	BASE PINS	7
NOMINAL HEATER	6.3 V / 300 mA	PARALLEL HEATER	— / —
HEATING	Indirect	SERIES OPERATION	Not specified
CATHODE ARRANGEMENT	Separate cathodes	SECTION CONSTRUCTION	Similar

SECTION RATINGS

SECTION1 Pentode	
TRANSCONDUCTANCE	0.0065 S
MAXIMUM PLATE VOLTAGE	150 V
MAXIMUM SCREEN VOLTAGE	150 V
MAXIMUM PLATE DISSIPATION	2.1 W
MAXIMUM SCREEN DISSIPATION	1.5 W
MAXIMUM CATHODE CURRENT	30 mA
<i>Promoted ratings and characteristics translated from the filename-designated Russian entry only.</i>	

The 6J10BVR is a Russian ruggedized long-life double-control high-frequency pentode for RF amplification and frequency conversion. The source entry was translated to English and processed independently from neighboring partial entries.

SOURCE OPERATING CONDITIONS

[SOURCE PDF](#)

1981 Russian Tubes Katsnelson and Larionov

Published test conditions and operating points. Values on this page are preserved as reported by this source.

1981 RUSSIAN TUBES KATSNELSON AND LARIONOV

Section 1 · Pentode

CHARACTERISTICS		
PARAMETER	PUBLISHED VALUE	CONDITION / NOTE
Guaranteed service life	2000 h	Published source value
Nominal heater voltage	6.3 V	Published source value
Nominal heater current	300 mA	Published source value
Transconductance	6500 μS	Published operating point

TUBE TINKER

An independent reference for electronic tubes, vacuum tubes,
and their source documents.

[Catalog](#) [Tube types](#) [Full books](#) [Blog](#) [Feedback & corrections](#)

© 2026 Tube Tinker