



ELECTRONIC TUBE REFERENCE

6J10P

Voltage - Radio Detector Converter electronic tube

CONSOLIDATED TECHNICAL DATA

1 SECTION

CONSTRUCTION

PENTODE

Russian wideband high-frequency pentode for RF voltage amplification and frequency conversion. High transconductance and long rated service life suit professional broadband amplifier and converter applications.

GENERAL CHARACTERISTICS

BASE DESIGNATION	—	BASE PINS	9
NOMINAL HEATER	6.3 V / 300 mA	PARALLEL HEATER	— / —
HEATING	Indirect	SERIES OPERATION	Not specified
CATHODE ARRANGEMENT	Separate cathodes	SECTION CONSTRUCTION	Similar

SECTION RATINGS

SECTION 1 Pentode	
PLATE RESISTANCE	100000 Ω
TRANSCONDUCTANCE	0.01 S
MAXIMUM PLATE VOLTAGE	250 V
MAXIMUM SCREEN VOLTAGE	120 V
MAXIMUM PLATE DISSIPATION	3 W
MAXIMUM SCREEN DISSIPATION	0.75 W
MAXIMUM CATHODE CURRENT	35 mA
<i>Promoted ratings and characteristics translated from the filename-designated Russian entry only.</i>	

The 6J10P is a Russian wideband high-frequency pentode for RF voltage amplification and frequency conversion. The source entry was translated to English and processed independently from neighboring partial entries.

SOURCE OPERATING CONDITIONS

[SOURCE PDF](#)

1981 Russian Tubes Katsnelson and Larionov

Published test conditions and operating points. Values on this page are preserved as reported by this source.

1981 RUSSIAN TUBES KATSNELSON AND LARIONOV

Section 1 · Pentode

CHARACTERISTICS		
PARAMETER	PUBLISHED VALUE	CONDITION / NOTE
Guaranteed service life	5000 h	Published source value
Nominal heater voltage	6.3 V	Published source value
Nominal heater current	300 mA	Published source value
Transconductance	10000 μS	Published operating point
Plate resistance	100000 Ohm	Published operating point

TUBE TINKER

An independent reference for electronic tubes, vacuum tubes,
and their source documents.

[Catalog](#) [Tube types](#) [Full books](#) [Blog](#) [Feedback & corrections](#)

© 2026 Tube Tinker