



ELECTRONIC TUBE REFERENCE

6J9P

Voltage Pentode - High Frequency (single) electronic tube

CONSOLIDATED TECHNICAL DATA

1 SECTION

CONSTRUCTION

PENTODE

Russian high-transconductance miniature wideband pentode. Designed for broadband voltage amplification, it combines substantial transconductance with compact construction for high-frequency signal stages requiring wide frequency response.

GENERAL CHARACTERISTICS

BASE DESIGNATION	—	BASE PINS	9
NOMINAL HEATER	6.3 V / 300 mA	PARALLEL HEATER	— / —
HEATING	Indirect	SERIES OPERATION	Not specified
CATHODE ARRANGEMENT	Separate cathodes	SECTION CONSTRUCTION	Similar

SECTION RATINGS

SECTION 1 Pentode	
TRANSCONDUCTANCE	0.0175 S
MAXIMUM PLATE VOLTAGE	250 V
MAXIMUM SCREEN VOLTAGE	150 V
MAXIMUM SCREEN DISSIPATION	0.75 W
MAXIMUM CATHODE CURRENT	35 mA
<i>Promoted values translated from the complete filename-designated Russian entry only.</i>	

The 6J9P is a Russian high-transconductance miniature wideband pentode. The source entry was translated to English and processed independently from neighboring partial entries.

SOURCE OPERATING CONDITIONS

[SOURCE PDF](#)

1981 Russian Tubes Katsnelson and Larionov

Published test conditions and operating points. Values on this page are preserved as reported by this source.

1981 RUSSIAN TUBES KATSNELSON AND LARIONOV

Section 1 · Pentode

CHARACTERISTICS		
PARAMETER	PUBLISHED VALUE	CONDITION / NOTE
Nominal heater voltage	6.3 V	Published source value
Nominal heater current	300 mA	Published source value
Transconductance	17500 μ S	Published operating point