ELECTRONIC TUBE REFERENCE

6X5G

Rectifier - Full Wave electronic tube

CONSOLIDATED TECHNICAL DATA
2 SECTIONS
CONSTRUCTION
RECTIFIER-RECTIFIER

Glass-envelope indirectly heated full-wave high-vacuum rectifier for capacitor-input or choke-input supplies. Its 6.3 V heater provides conventional moderate-current power-supply rectification.

General characteristics

BASE DESIGNATION	8	**BASE PINS**	6
NOMINAL HEATER	6.3 V / 600 mA	**PARALLEL HEATER**	— / —
HEATING	Indirect	**SERIES OPERATION**	Not specified
CATHODE ARRANGEMENT	Common cathode	**SECTION CONSTRUCTION**	Similar

Section ratings

SECTION1 Rectifier

PEAK INVERSE VOLTAGE	1250 V
NOMINAL OUTPUT CURRENT	70 mA
PEAK FORWARD CURRENT	210 mA
FORWARD VOLTAGE DROP	22 V
MAXIMUM HEATER-CATHODE VOLTAGE	450 V

Promoted from clearly identified printed ratings/characteristics; additional operating points and capacitances retained in TUBE_SECTION_PARAMETER.

SECTION2 Rectifier

PEAK INVERSE VOLTAGE	1250 V
NOMINAL OUTPUT CURRENT	70 mA
PEAK FORWARD CURRENT	210 mA
FORWARD VOLTAGE DROP	22 V
MAXIMUM HEATER-CATHODE VOLTAGE	450 V

Second physical rectifier section; electrical properties populated from corresponding identical section.

> Full-wave high-vacuum rectifier for capacitor-input or choke-input filter service.

SOURCE OPERATING CONDITIONS

1937 Raytheon Radio Receiving Tubes

SOURCE PDF

Published test conditions and operating points. Values on this page are preserved as reported by this source.

1937 RAYTHEON RADIO RECEIVING TUBES

Section 1 · Rectifier

OTHER		
PARAMETER	**PUBLISHED VALUE**	**CONDITION / NOTE**
Heater voltage	**6.3 V**	Section1
Heater current	**600 mA**	Section1
RMS AC voltage per plate maximum	**325 V**	FullWave
Peak inverse voltage maximum	**1250 V**	FullWave
DC output current maximum	**70 mA**	FullWave
Maximum heater-cathode DC voltage	**450 V**	FullWave

CHARACTERISTIC		
PARAMETER	**PUBLISHED VALUE**	**CONDITION / NOTE**
Average tube voltage drop	**22 V**	At75mAOutputCurrentPerPlate

SOURCE DATA APPENDIX

SOURCE OPERATING CONDITIONS

1948 Brimar Radio Valve Manual

SOURCE PDF

Published test conditions and operating points. Values on this page are preserved as reported by this source.

1948 BRIMAR RADIO VALVE MANUAL

Section 1 · Rectifier

OTHER		
PARAMETER	**PUBLISHED VALUE**	**CONDITION / NOTE**
RMS Input per Anode	**325 V**	CapacitorInputFilter

PARAMETER	PUBLISHED VALUE	CONDITION / NOTE
Supply Impedance per Anode	**150 ohm**	CapacitorInputFilter; minimum
Reservoir Condenser	**32 uF**	CapacitorInputFilter; maximum

SOURCE OPERATING CONDITIONS

1950 Sylvania

Published test conditions and operating points. Values on this page are preserved as reported by this source.

1950 SYLVANIA

Section 1 · Rectifier

APPLICATION		
PARAMETER	**PUBLISHED VALUE**	**CONDITION / NOTE**
Filter service	**Capacitor-input or choke-input**	—

SOURCE DATA APPENDIX

SOURCE OPERATING CONDITIONS

SOURCE PDF

1958 Brimar Radio Valve No 7

Published test conditions and operating points. Values on this page are preserved as reported by this source.

1958 BRIMAR RADIO VALVE NO 7

Section 1 · Rectifier

CHARACTERISTIC		
PARAMETER	**PUBLISHED VALUE**	**CONDITION / NOTE**
Heater Voltage	**6.3 V**	—
Heater Current	**600 mA**	—

SOURCE DATA APPENDIX

SOURCE OPERATING CONDITIONS

1961 Tung Sol

Published test conditions and operating points. Values on this page are preserved as reported by this source.

1961 TUNG SOL

Section 1 · Rectifier

OTHER		
PARAMETER	**PUBLISHED VALUE**	**CONDITION / NOTE**
Heater voltage	**6.3 V**	Nominal
Heater current	**600 mA**	Nominal
AC plate voltage per plate RMS	**325 V**	CapacitorInputFilter
DC output current	**70 mA**	CapacitorInputFilter
AC plate voltage per plate RMS	**450 V**	ChokeInputFilter
DC output current	**70 mA**	ChokeInputFilter
Input choke	**8 H**	ChokeInputFilter
Total effective plate supply impedance per plate	**150 ohm**	CapacitorInputFilter

Tube Tinker

An independent reference for electronic tubes, vacuum tubes, and their source documents.

Catalog Tube types Full books Blog Feedback & corrections

© 2026 Tube Tinker