



ELECTRONIC TUBE REFERENCE

GL869B

Rectifier - Half Wave electronic tube

CONSOLIDATED TECHNICAL DATA

1 SECTION
CONSTRUCTION
RECTIFIER

General Electric mercury-vapor half-wave rectifier specifically used in broadcast-transmitter power supplies, providing high-voltage multi-ampere DC output with low arc drop.

GENERAL CHARACTERISTICS

BASE DESIGNATION	—	BASE PINS	—
NOMINAL HEATER	5 V / 18 A	PARALLEL HEATER	— / —
HEATING	Direct	SERIES OPERATION	Not specified
CATHODE ARRANGEMENT	Separate cathodes	SECTION CONSTRUCTION	Similar

SECTION RATINGS

SECTION1 Rectifier	
PEAK INVERSE VOLTAGE	20000 V
NOMINAL OUTPUT CURRENT	5 A
PEAK FORWARD CURRENT	15 A
FORWARD VOLTAGE DROP	15 V
WARM-UP TIME	60 s

Half-wave mercury-vapor rectifier for broadcast-transmitter service with in-phase or quadrature filament excitation.

SOURCE OPERATING CONDITIONS

[SOURCE PDF](#)

1968 General Electric Co

Published test conditions and operating points. Values on this page are preserved as reported by this source.

1968 GENERAL ELECTRIC CO

Section 1 · Rectifier

CHARACTERISTIC		
PARAMETER	PUBLISHED VALUE	CONDITION / NOTE
Heating Time	1 min	Typical

OTHER		
PARAMETER	PUBLISHED VALUE	CONDITION / NOTE
MaximumInstantaneousAnodeCurrent	15 A	QuadratureOperation
Maximum Surge Anode Current	100 A	—

TUBE TINKER

An independent reference for electronic tubes, vacuum tubes,
and their source documents.

[Catalog](#) [Tube types](#) [Full books](#) [Blog](#) [Feedback & corrections](#)

© 2026 Tube Tinker