

ELECTRONIC TUBE REFERENCE

RS1036L

Power - Tetrode (NOT beam) (over 1000V 100W) electronic tube

CONSOLIDATED TECHNICAL DATA

1 SECTION
CONSTRUCTION
TETRODE

Coaxial metal-ceramic tetrode with resonance suppression for high-power television transmitters.

GENERAL CHARACTERISTICS

BASE DESIGNATION	—	BASE PINS	—
NOMINAL HEATER	4.5 V / 200 A	PARALLEL HEATER	— / —
HEATING	Direct	SERIES OPERATION	Not specified
CATHODE ARRANGEMENT	Separate cathodes	SECTION CONSTRUCTION	Similar

SECTION RATINGS

SECTION1 Tetrode	
TRANSCONDUCTANCE	0.12 S
AMPLIFICATION FACTOR	7.5
MAXIMUM PLATE VOLTAGE	7000 V
MAXIMUM SCREEN VOLTAGE	1000 V
MAXIMUM PLATE DISSIPATION	20000 W
MAXIMUM CATHODE CURRENT	6 A
Ratings, characteristics, and operating tables audited semantically; repeated identical systems represented once where applicable.	

Coaxial metal-ceramic tetrode with integrated resonance suppression for TV transmitters,

SOURCE OPERATING CONDITIONS

[SOURCE PDF](#)

1963 Siemens

Published test conditions and operating points. Values on this page are preserved as reported by this source.

1963 SIEMENS

Section 1 · Tetrode

OTHER		
PARAMETER	PUBLISHED VALUE	CONDITION / NOTE
Heater voltage UF 4,5 V	—	—
at UA = UG2 = UG1 = 300 V	—	—
at UA = 2 kV,	—	—
UG2 = 500 to 800 V,	—	—
at UA = 2 kV,	—	—
UG2 = 800 V,	—	—
Frequency f 960 MHz	—	—
Anode voltage (dc) UA 7,0 kV	—	—
Screen grid voltage (dc) UG2 1000 V	—	—
Control grid voltage (dc) UG1 – 200 V	—	—
Anode dissipation PA 20 kW	—	—
Screen grid dissipation PG2 180 W	—	—
Control grid dissipation PG1 80 W	—	—
Frequency f 470 ... 800 MHz	—	—
Anode voltage (dc) UA 6,0 kV	—	—
Screen grid voltage (dc) UG2 800 V	—	—
Control grid voltage (dc) UG1 – 112 V	—	—
Anode dissipation, black level PA SW 14,6 kW	—	—

PARAMETER	PUBLISHED VALUE	CONDITION / NOTE
Frequency f 960 MHz	—	—
Anode voltage (dc) UA 7,0 kV	—	—
Screen grid voltage (dc) UG2 1000 V	—	—
Control grid voltage (dc) UG1 – 200 V	—	—
Anode dissipation PA 20 kW	—	—
Screen grid dissipation PG2 180 W	—	—
Control grid dissipation PG1 80 W	—	—
Frequency f 470 ... 800 MHz	—	—
Anode voltage (dc) UA 6,4 kV	—	—
Screen grid voltage (dc) UG2 800 V	—	—
Control grid voltage (dc) UG1 – 112 V	—	—
Anode dissipation, black level PA SW 19 kW	—	—
UG1 = f (UA) Parameter = IA	—	—
UG2 = 800 V Parameter = IG2	—	—

CURRENT		
PARAMETER	PUBLISHED VALUE	CONDITION / NOTE
Heater current IF $\approx$ 200 A	—	—
Emission current I em 45 A	—	—
IA = 3 A	—	—
Cathode current (dc) IK 6,0 A	—	—
Peak cathode current IK M 30 A	—	—
Zero-signal anode current (dc) IA 0 1,8 A	—	—
Anode current (dc), black level I A SW 3,7 A	—	—
Screen grid current (dc), black level I G2 SW 90 mA	—	—

PARAMETER	PUBLISHED VALUE	CONDITION / NOTE
Cathode current (dc) IK 6,0 A	—	—
Peak cathode current IK M 30 A	—	—
Zero-signal anode current (dc) IA 0 2,2 A	—	—
Anode current (dc), black level I A SW 5,0 A	—	—
Screen grid current (dc), black level I G2 SW 140 mA	—	—
Ø 0,12 mm should be used to test the anode overcurrent trip circuit.	—	—

CHARACTERISTIC		
PARAMETER	PUBLISHED VALUE	CONDITION / NOTE
Amplification factor of screen grid μ_{g1} 7,5	—	—
Transconductance s 120 mA/V	—	—

TUBE TINKER

An independent reference for electronic tubes, vacuum tubes, and their source documents.

[Catalog](#) [Tube types](#) [Full books](#) [Blog](#) [Feedback & corrections](#)

© 2026 Tube Tinker