



²⁾ A componente contínua pode ser 100 V, no máximo.

Valores limites do heptodo

V_{ao}	= max	550	V
V_a	= max	300	V
W_a	= max	1,7	W
$V_{(g2+g4)}$	= max	550	V
V_{g2+g4}	= max	125	V
$V_{g2+g4} (I_a < 1 \text{ mA})$	= max	300	V
W_{g2+g4}	= max	1	W
I_k	= max	12,5	mA
R_{g1}	= max	3	M Ω
R_{g3}	= max	3	M Ω
R_{kf}	= max	20	k Ω
V_{kf}	= max	150	V ¹⁾
$V_{g1} (I_{g1} = +0,3 \mu\text{A})$	= max	-1,3	V
$V_{g3} (I_{g3} = +0,3 \mu\text{A})$	= max	-1,3	V

¹⁾ A componente contínua pode ser 100 V, no máximo.

