

RADIO MANUFACTURERS ASSOCIATION

#98

November 27th, 1936

To Tube Engineer:

RMA Tube Standardization Release #98 re 1V1.

The 1V1 is a ballast tube having a 1 volt drop and a current rating of 500 ma. The tube is enclosed in an ST-12 bulb and is based with a small 4-pin base. The connections and dimensions are as follows:

Pin #1	Filament
Pin #2	Blank
Pin #3	Blank
Pin #4	Filament

Maximum Overall Length	4-1/4"
Maximum Diameter	1-9/16"

RMA basing number 4A

As this tube is well known to the industry it is not necessary that this committee distribute samples to the manufacturers.

This information is furnished you through the courtesy of the National Union Radio Corporation.

Very truly yours,

Edmond H. Wiley
Chairman
Tube Numbering