



TYPE	DESCRIPTION	CHARACTERISTICS SIMILAR TO	BASING
1AD2	HV Diode	1J3 HV Rect.	12DQ
2AH2	HV Diode	3A3 HV Rect.	12DG
2AS2	HV Diode	2AH2 HV Rect.	12EW
3AT2	HV Diode	3A3 HV Rect.	12EX
4HA7	Dissimilar	12AU7 (Pins 4, 9, 10)	12FQ
6AF11	Double Triode	plus 12AX7	12DP
6AG11	Dissimilar	Hi-Mu Tri. (Pins 5, 6, 8) plus 6CX8	12DA
6AL11	Duplex-Diode	12AT7 Twin Tri. plus 6BW8 Di. with Sep. Cath.	12BU
6AR11	Twin Triode	6DT6 (Pins 2, 3, 4, 6, 7) plus 6AQ5	12DM
6AS11	Double Pentode	Two 6GM6 Pent.	12DP
6AV11	Dissimilar	Hi-Mu Tri. (Pins 5, 6, 8) plus 6CX8	12BY
6AX3	Dbl.-Tri. Pent.	Three 12AU7 Tri.	12BL
6AY11	Triple Triode	6AX4-GTB Damp. Di.	12DA
6B10	Diode	12AX7 Twin Tri.-plus 6BW8 Di. with Sep. Cath.	12BF
6BA11	Duplex-Diode	12AU7 Twin Triode	12ER
6BD11	Twin Triode	plus 6BW8 Diode	12DP
6BE3	Tri-Twn. Pent.	6HS8 plus Medium Mu Tri.	12BL
6BF11	Dissimilar	Med. Mu Tri. (Pins 3, 4, 7), High-Mu Tri. (Pins 5, 6, 8), plus Video Pent.	12EZ
6BH11	Diode	Damper—Max. Ratings: PIV=5000V. DC Output =200 ma.	12FP
6BJ3	Double Pentode	6DT6 (Pins 2, 3, 5, 6, 7) plus Power Output Pent.	12BL
6C10	Twin-Triode	Two 6GH8 Triodes	12BQ
6D10	Pentode	plus 6GH8 Pent.	12BY
6FJ7	Diode	6W4-GT Damper	12BM
6FM7	Triple Triode	Three 12AX7 Triodes	12EJ
6FY7	Triple Triode	12AT7 Triodes	12EO
6G11	Dissimilar	6DN7 Vert. Osc. (Pins 9, 10, 11) and Amp.	12BU
6GE5	Double Triode	6EA7 Vert. Osc. (Pins 9, 10, 11) and Amp.	12BJ
6GF5	Dissimilar	6DR7 Vert. Osc. (Pins 9, 10, 11) and Amp.	12BJ
6GV5	Double Triode	6DT6 (Pins 2, 3, 4, 6, 7) plus 6CU5	12DR
6GY5	Dissimilar	6DQ6-B Hor. Defl. Amp.	12DG
6HB5	Beam Pentode	6DQ6-B Hor. Defl. Amp.	12DM
6HD5	Beam Pentode	6DQ6-B Hor. Defl. Amp.—Max. Ratings: Plate Dis.=18 W, DC Cath. Cur.=230 ma.	6AF11, 6AS11, 6BD11, 15AF11, 15BD11
6HE5	Beam Pentode	6GY5 Hor. Defl. Amp.	12DQ
6HF5	Beam Pentode	Hor. Defl. Amp.—Max. Ratings: Plate Dis.=24 W, DC Cath. Cur.=280 ma.	12ER
6J10	Beam Pentode	6E25 Vert. Defl. Amp.	12ES
6J11	Beam Pentode	6DQ5 Hor. Defl. Amp.	12EZ
6J28	Pentode-Gated Beam Disc.	6BN6 plus 6AL11 Power Out. Pent.	12FB
6K11	Twin Pentode	Two 6EW6 Pent.	12BT
6M11	Triode-Pentode	6SN7 Tri. plus 12R5 Pent.	12BW
6Q11	Three Section Triode	One 12AU7 (Pins 4, 9, 10) plus two 12AX7	12DZ
6T10	Triode-Pentode	Two 12AT7 plus 6EW6 Pent.	12BY
6U10	Dis. Dbl. Pent.	6K11	12CA
8B10	Dis. Dbl. Pent.	6AL11 Power Pent. plus one 12AX7	12BY
10AL11	Dis. Dbl. Pent.	6AL11	12FM
11AR11	Dis. Dbl. Pent.	6AL11	12EZ
12AL11	Dis. Dbl. Pent.	One 12AX7 (Pins 5, 6, 7) plus two 12AU7	12FE
12AX3	Diode	6B10	12BF
12BE3	Diode	6AL11	12BU
12BT3	Diode	6AR11	12DM
12GE5	Beam Pentode	6AL11	12BU
13J10	Pentode-Gated Beam Disc.	6AX3	12BL
15AF11	Dis. Dbl. Tri.	6BE3	12BL
15BD11	Dbl.-Tri. Pent.	6W4-GTA	12BL
15FM7	Dis. Dbl. Tri.	6GE5	12BJ
15FY7	Dis. Dbl. Tri.	6J10	12BT
16GY5	Beam Pentode	6AF11	12DP
17AX3	Diode	6BD11	12DP
17BE3	Diode	6FM7	12EJ
17BF11	Dis. Dbl. Pent.	6FY7	12EO
17GE5	Beam Pentode	6GY5	12DR
17GV5	Beam Pentode	6AX3	12BL
17JZ8	Triode-Pentode	6BE3	12BL
21GY5	Beam Pentode	6BF11	12EZ
21HB5	Beam Pentode	6GE5	12BJ
21HB5-A	Beam Pentode	6GV5	12DR
21HJ5	Beam Pentode	6JZ8	12DZ
22B9	Diode	6GY5	12FB
22BW3	Dis. Dbl.-Tri. Pent.	6HB5	12BJ
30AG11	Duplex-Diode	6HB5	12BJ
33G17	Diode-Pentode	6DQ5 with Ext. Conn. to Suppressor	12FL
33GY7	Diode-Pentode	22DE4	12BL
38HE7	Diode-Pentode	6JZ8 plus Med.-Mu Tri. (Pins 7, 10, 11)	12FT
7984	Beam Pentode	6AC11	12DA
8156	Beam Pentode	6GE5 plus 6AX3	12FC
		6GE5 plus 6AX3	12FN
		6HB5 plus 6BJ3	12FS
		6146	12EU
		R-F Power Amp.—21 W Output (1MS) at 175 Mc	12EU


COMPACTRONS




12BF
6B10, 8B10




12BJ
6GE5, 6GF5, 6HB5
12GE5, 17GE5, 21HB5,
21HB5A




12BL
6AX3, 6BE3, 6BJ3,
12AX3, 12BE3, 12BT3,
17AX3, 17BE3, 22BW3




12BM
6FJ7




12BQ
6C10




12BT
6J10, 13J10




12BU
6AL11, 6G11
10AL11, 12AL11




12BW
6J11




12BY
6AV11, 6D10,
6K11, 6Q11




12CA
6M11




12DA
6AG11, 6AY11, 30AG11




12DB
6DQ6-B Hor. Defl. Amp.,
12DB, 6DQ6-B Hor. Defl. Amp.,
12DR




12DG
2AH2




12DM
6AR11, 11AR11




12DQ
1AD2




12DR
6GV5, 6GY5, 16GY5,
17GV5, 21GY5




12DZ
6JZ8, 17JZ8




12EJ
6FM7, 15FM7




12EO
6FY7, 15FY7




12ER
6BA11




12ES
6HD5




12EU
7984, 8156




12EW
2AS2




12EX
3AT2




12EY
6HE5




12EZ
6BF11, 6T10, 17BF11




12FB
6HF5




12FC
33GT7




12FE
6U10




12FL
21HJ5




12FM
6T9




12FN
33GY7




12FP
6BH11



12FQ
4HA7



12FS
38HE7



12FT
23Z9