



**EZ80/
6V4**

Current Equipment Type



TYPE EZ80/6V4
MINIATURE
FULL-WAVE
RECTIFIER



Heater Voltage	...	...	...	...	...	...	6.3 volts
Heater Current	...	...	...	...	...	...	0.6 amp.

RATINGS

Peak Inverse Voltage	...	...	...	...	...	980 volts max.
Peak Current (each anode)	...	...	...	...	...	270 mA max.
Hot Switching Transient Anode Current	...	...	...	...	...	900 mA max.
Peak Heater-Cathode potential	...	...	...	...	...	500 volts max.

CHARACTERISTICS AS FULL-WAVE RECTIFIER

CONDENSER INPUT

R.M.S. Input per Anode	...	250	275	300	350 volts
Supply Impedance per Anode	...	125	175	215	300 ohms min.
Reservoir Condenser	...	50	50	50	50 μ F max.
Rectified Current	...	90	90	90	90 mA max.

