



ELECTRONIC TUBE REFERENCE

6N17BVR

Voltage - Dual Triode (similar) electronic tube

CONSOLIDATED TECHNICAL DATA

2 SECTIONS

CONSTRUCTION

TRIODE-TRIODE

Russian double triode designed for low-frequency voltage amplification, with paired triode sections intended for compact small-signal electronic circuitry.

GENERAL CHARACTERISTICS

BASE DESIGNATION	—	BASE PINS	—
NOMINAL HEATER	6.3 V / 370 mA	PARALLEL HEATER	— / —
HEATING	Indirect	SERIES OPERATION	Not specified
CATHODE ARRANGEMENT	Separate cathodes	SECTION CONSTRUCTION	Similar

SECTION RATINGS

SECTION1 Triode	
TRANSCONDUCTANCE	0.004 S
AMPLIFICATION FACTOR	70
MAXIMUM PLATE VOLTAGE	250 V
MAXIMUM PLATE DISSIPATION	0.9 W
MAXIMUM CATHODE CURRENT	10 mA
Two electrically identical triodes; represented by one section row under identical-section compression.	

SECTION2 Triode	
TRANSCONDUCTANCE	0.004 S
AMPLIFICATION FACTOR	70
MAXIMUM PLATE VOLTAGE	250 V
MAXIMUM PLATE DISSIPATION	0.9 W
MAXIMUM CATHODE CURRENT	10 mA
<i>Second identical physical triode section; added to align rows with SectionCount.</i>	

Double triode for low-frequency voltage amplification.

SOURCE OPERATING CONDITIONS

[SOURCE PDF](#)

1981 Russian Tubes Katsnelson and Larionov

Published test conditions and operating points. Values on this page are preserved as reported by this source.

1981 RUSSIAN TUBES KATSNELSON AND LARIONOV

Section 1 · Triode

CHARACTERISTIC		
PARAMETER	PUBLISHED VALUE	CONDITION / NOTE
Heater voltage	6.3 V	Published nominal heater condition.
Heater current	370 mA	Published heater current.
Plate current	3.3 mA	Published basic-parameter operating point.
Transconductance	4000 μ S	Published basic-parameter value; normalized to μ S.
Amplification factor	70	Published basic-parameter value.
Service life	2000 h	Published service-life figure.

OTHER		
PARAMETER	PUBLISHED VALUE	CONDITION / NOTE
Maximum plate voltage	250 V	Published limiting operating value.
Maximum cathode current	10 mA	Published limiting cathode-current value.
Maximum plate dissipation	0.9 W	Published per-triode plate dissipation.

TUBE TINKER

An independent reference for electronic tubes, vacuum tubes,
and their source documents.

[Catalog](#) [Tube types](#) [Full books](#) [Blog](#) [Feedback & corrections](#)

© 2026 Tube Tinker