



ELECTRONIC TUBE REFERENCE

IN18

Nixie electronic tube

CONSOLIDATED TECHNICAL DATA

1 SECTION
CONSTRUCTION
NIXIE

Russian cold-cathode glow-discharge numeric/symbol indicator for direct visual display. Documentation specifies ignition voltage up to 170 V and a published life of at least 5,000 hours, with operating data for both DC and pulsating supplies.

GENERAL CHARACTERISTICS

BASE DESIGNATION	—	BASE PINS	—
NOMINAL HEATER	— / —	PARALLEL HEATER	— / —
HEATING	Indirect; cold cathode	SERIES OPERATION	Not specified
CATHODE ARRANGEMENT	Separate cathodes	SECTION CONSTRUCTION	Similar

SECTION RATINGS

SECTION 1 Nixie	
MAXIMUM REGULATOR CURRENT	4 A
STARTING VOLTAGE	170 V
MAINTAINING VOLTAGE	150 V
<i>Single cold-cathode glow-discharge indicator section; Nixie-specific operating data are also retained as parameters.</i>	

The IN18 is a Russian cold-cathode glow-discharge Nixie numeric/symbol display intended for visual indication. Ignition voltage up to 170 v, maintaining/anode-cathode voltage up to 150 v, published life at least 5000 h. The supplied Russian datasheet was translated for this record.

SOURCE OPERATING CONDITIONS

[SOURCE PDF](#)

196X Nixie Russian 2

Published test conditions and operating points. Values on this page are preserved as reported by this source.

196X NIXIE RUSSIAN 2

Section 1 · Nixie

OTHER		
PARAMETER	PUBLISHED VALUE	CONDITION / NOTE
DC operating current	4–7 mA	DC supply
Pulsating operating current average	2–4 mA	50 Hz pulsating supply
Supply voltage	200— V	Minimum stated source/supply voltage
Ignition voltage	—170 V	Published datasheet value
Maintaining voltage / anode-cathode drop	—150 V	Published datasheet value
Indication current	—4 mA	Published datasheet value

CHARACTERISTIC		
PARAMETER	PUBLISHED VALUE	CONDITION / NOTE
Brightness	50— cd/m ²	Minimum
Viewing angle	90— deg	Minimum
Service life	5000— h	Minimum

TUBE TINKER

An independent reference for electronic tubes, vacuum tubes, and their source documents.

[Catalog](#) [Tube types](#) [Full books](#) [Blog](#) [Feedback & corrections](#)

© 2026 Tube Tinker