

ELECTRONIC TUBE REFERENCE

PT625

Power - Pentode (NOT beam) electronic tube

CONSOLIDATED TECHNICAL DATA

1 SECTION
CONSTRUCTION
PENTODE

Marconi super-power pentode for higher-output audio service at anode voltages to approximately 250 V.

GENERAL CHARACTERISTICS

BASE DESIGNATION	—	BASE PINS	5
NOMINAL HEATER	6 V / 250 mA	PARALLEL HEATER	— / —
HEATING	Direct	SERIES OPERATION	Not specified
CATHODE ARRANGEMENT	Separate cathodes	SECTION CONSTRUCTION	Similar

SECTION RATINGS

SECTION1 Pentode	
PLATE RESISTANCE	43000 Ω
TRANSCONDUCTANCE	0.00185 S
MAXIMUM PLATE VOLTAGE	250 V
MAXIMUM SCREEN VOLTAGE	200 V
Published ratings/characteristics promoted from the approved datasheet where legible.	

Super-power pentode for anode voltages up to 250 V.

TUBE TINKER

An independent reference for electronic tubes, vacuum tubes,
and their source documents.

[Catalog](#) [Tube types](#) [Full books](#) [Blog](#) [Feedback & corrections](#)

© 2026 Tube Tinker