

Tunable X-band integral-cavity TR gas-discharge cell with primer electrode and preset tuning, designed for radar receiver protection.

GENERAL CHARACTERISTICS

BASE DESIGNATION	—	BASE PINS	—
NOMINAL HEATER	— / —	PARALLEL HEATER	— / —
HEATING	Indirect; cold cathode	SERIES OPERATION	Not specified
CATHODE ARRANGEMENT	Separate cathodes	SECTION CONSTRUCTION	Similar

SECTION RATINGS

SECTION 1 Microwave TR Switch

No fixed ratings recorded.

Microwave T.R. gas-discharge cell; device-specific primer, breakdown, leakage, recovery, frequency and power data are retained in parameter rows.

Ferranti QF41A is an X-band tuneable integral-cavity T.R. gas-discharge cell for branched duplexers in WG16 waveguide. A primer electrode supports rapid firing, and the sheet specifies 50 kW peak power plus leakage and recovery limits.

SOURCE OPERATING CONDITIONS

[SOURCE PDF](#)

1963 Ferranti

Published test conditions and operating points. Values on this page are preserved as reported by this source.

1963 FERRANTI

Section 1 · Microwave TR Switch

OTHER		
PARAMETER	PUBLISHED VALUE	CONDITION / NOTE
Maximum transmitter power	50 kW	Peak
Primer supply voltage	-1500--700 V	Negative D.C. supply limits
Primer current	100-200 uA	Primer electrode

CHARACTERISTIC		
PARAMETER	PUBLISHED VALUE	CONDITION / NOTE
Preset tuning span	75 Mc/s	Approximately ± 75 Mc/s
Loaded Q	125-160	Low power
VSWR at resonance	—1.4	Low power; average and limit
Insertion loss	—1.2 dB	Low power; average and limit
Flat leakage power	—30 mW	40 kW high-power test
Spike leakage energy	—0.1 erg/pulse	40 kW high-power test
Breakdown power	—250 mW	High power
Recovery time to -6 dB	—4 us	High power
Primer operating voltage	250-450 V	Approximate operating range from table

FREQUENCY		
PARAMETER	PUBLISHED VALUE	CONDITION / NOTE
Operating frequency	9005-9155 Mc/s	QF41A suffix range

TUBE TINKER

An independent reference for electronic tubes, vacuum tubes,
and their source documents.

[Catalog](#) [Tube types](#) [Full books](#) [Blog](#) [Feedback & corrections](#)

© 2026 Tube Tinker