

ELECTRONIC TUBE REFERENCE

SRS457

Power - Tetrode (NOT beam) (over 1000V 100W) electronic tube

CONSOLIDATED TECHNICAL DATA

1 SECTION
CONSTRUCTION
TETRODE

Transmitting power tetrode designed for RF amplification, communications, industrial RF generation, oscillation, modulation, or frequency multiplication.

GENERAL CHARACTERISTICS

BASE DESIGNATION	—	BASE PINS	—
NOMINAL HEATER	6.3 V / 10 A	PARALLEL HEATER	— / —
HEATING	Direct	SERIES OPERATION	Not specified
CATHODE ARRANGEMENT	Separate cathodes	SECTION CONSTRUCTION	Similar

SECTION RATINGS

SECTION1 Tetrode	
TRANSCONDUCTANCE	0.0055 S
MAXIMUM PLATE VOLTAGE	5000 V
MAXIMUM SCREEN VOLTAGE	700 V
MAXIMUM PLATE DISSIPATION	500 W
MAXIMUM SCREEN DISSIPATION	65 W
MAXIMUM GRID DISSIPATION	25 W
MAXIMUM CATHODE CURRENT	600 mA
Promoted ratings/characteristics are source-published values; additional published values and operating examples are preserved in the parameter table.	

SRS457 is a radiation-cooled transmitting tetrode intended for communications, industrial RF generators, audio-frequency amplification. The source publishes heater data, static characteristics, operating examples, limiting ratings, capacitances, and mechanical or cooling requirements as applicable.



SOURCE OPERATING CONDITIONS

[SOURCE PDF](#)

1953 RFT Rundfunk Technik

Published test conditions and operating points. Values on this page are preserved as reported by this source.

1953 RFT RUNDFUNK TECHNIK

Section 1 · Tetrode

OTHER		
PARAMETER	PUBLISHED VALUE	CONDITION / NOTE
HeaterVoltageNominal	10 V	Nominal
HeaterCurrentNominal	10 A	Nominal
Maximum Plate Voltage	5000 V	—
Maximum Screen Voltage	700 V	—
Maximum Plate Dissipation	500 W	—
Maximum Screen Dissipation	65 W	—
MaximumGridDissipation	25 W	—
Maximum Cathode Current	700 mA	—
Maximum Frequency	110 MHz	—

CHARACTERISTIC		
PARAMETER	PUBLISHED VALUE	CONDITION / NOTE
Transconductance	5500 μ S	Typical

TUBE TINKER

An independent reference for electronic tubes, vacuum tubes,
and their source documents.

[Catalog](#) [Tube types](#) [Full books](#) [Blog](#) [Feedback & corrections](#)

© 2026 Tube Tinker