



ELECTRONIC TUBE REFERENCE

YD1190

Power - Triode (over 1000V 100W) electronic tube

CONSOLIDATED TECHNICAL DATA

1 SECTION
CONSTRUCTION
TRIODE

Forced-air-cooled very-high-power RF triode for industrial oscillator service.

GENERAL CHARACTERISTICS

BASE DESIGNATION	—	BASE PINS	—
NOMINAL HEATER	8.4 V / 235 A	PARALLEL HEATER	— / —
HEATING	Direct	SERIES OPERATION	Not specified
CATHODE ARRANGEMENT	Separate cathodes	SECTION CONSTRUCTION	Similar

SECTION RATINGS

SECTION 1 Triode	
PLATE RESISTANCE	333.333 Ω
TRANSCONDUCTANCE	0.09 S
AMPLIFICATION FACTOR	30
MAXIMUM PLATE VOLTAGE	13000 V
MAXIMUM PLATE DISSIPATION	30000 W
MAXIMUM CATHODE CURRENT	14 A
High-power RF triode; published principal characteristic and limiting values promoted.	

Forced-air-cooled high-power RF triode for industrial oscillator service. Published filament, capacitance, limiting-rating, and representative Class-C industrial oscillator data were extracted from the supplied Philips sheet.

SOURCE OPERATING CONDITIONS

[SOURCE PDF](#)

1999 Philips E-Z

Published test conditions and operating points. Values on this page are preserved as reported by this source.

1999 PHILIPS E-Z

Section 1 · Triode

CHARACTERISTICS		
PARAMETER	PUBLISHED VALUE	CONDITION / NOTE
Filament voltage	8.4 V	—
Filament current	235 A	—
Transconductance	90000 μ S	—
Amplification factor	30	—

CAPACITANCE		
PARAMETER	PUBLISHED VALUE	CONDITION / NOTE
Anode to filament capacitance	1.3 pF	—
Grid to filament capacitance	100 pF	—
Anode to grid capacitance	45 pF	—

OTHER		
PARAMETER	PUBLISHED VALUE	CONDITION / NOTE
Maximum anode voltage	13000 V	—
Maximum anode current	14 A	—
Maximum anode dissipation	30000 W	—
Operating frequency	30 MHz	IndustrialClassC
Operating anode voltage	12000 V	IndustrialClassC;Frequency=30MHz
Operating anode current	12 A	IndustrialClassC;Frequency=30MHz
Anode output power	113000 W	IndustrialClassC;Frequency=30MHz
Frequency for full ratings	100 MHz	—

CONSTRUCTION		
PARAMETER	PUBLISHED VALUE	CONDITION / NOTE
Cooling system	ForcedAir	—

TUBE TINKER

An independent reference for electronic tubes, vacuum tubes,
and their source documents.

[Catalog](#) [Tube types](#) [Full books](#) [Blog](#) [Feedback & corrections](#)

© 2026 Tube Tinker